

# Power Rectifier 100 Amps & 150 Amps DO-8 case style

TYPE	MAX. CONT. VRRM VOLTAGE (VOLTS)	MAX. D.C. OUTPUT CURRENT (AMPS)	@ T <sub>c</sub> ( C)	1 CYCLE CURRENT SURGE (PEAK AMPS)
1N3288	100	100	130	1600
1N3288A	100	100	130	2300
1N3289	200	100	130	1600
1N3289A	200	100	130	2300
1N3290	300	100	130	1600
1N3290A	300	100	130	2300
1N3291	400	100	130	1600
1N3291A	400	100	130	2300
1N3292	500	100	130	1600
1N3292A	500	100	130	1600
1N3292B	500	100	130	2300
1N3293	600	100	130	1600
1N3293A	600	100	130	2300
1N3294	800	100	130	1600
1N3294A	800	100	130	2300
1N3295	1000	100	130	1600
1N3295A	1000	100	130	2300
1N3296	1200	100	130	1600
1N3296A	1200	100	130	2300
1N3297	1400	100	130	1600
1N3297A	1400	100	130	2300
1N4588	200	150	120	3000
1N4590	400	150	110	3000
1N4591	500	150	110	3000
1N4592	600	150	110	3000
1N4593	800	150	110	3000
1N4594	1000	150	110	3000
1N4595	1200	150	110	3000
1N4596	1400	150	110	3000
150A400	400	150	150	3000
150A600	600	150	150	3000
150A800	800	150	150	3000
150A1000	1000	150	150	3000
150A1200	1200	150	150	3000

NOTE: 1. Standard polarity is Cathode to Stud. For Anode to Stud add "R" to basic part number  
 2. Full datasheets available upon request.